HIRSCHMANN

MULTIMEDIA

MULTITAP

6-WAY



MFC 1861 Article number 695020464

PRODUCT CATEGORY: 20 CATV STATUS: AVAILABLE



Product

MULTITAP 6-WAY MFC 1861

Equipped with grounding connection, reinforced housing and F-connector socket. The multitap can be mounted both horizontally and vertically. Frequency range 5 -1218 MHz. This model contains 6 tap-ports and 1 loop through port. Also available with more or less tap ports. Supports return channel traffic. Always provide unused ports with a terminator (RFC 75, 947373001).

Properties	Certificates	Included
2 Year Warranty Screening Loss	A KY	N/A
1,2 GHz Ready MoCA Compliant Durability	CLASS	
		Tools
		- 1 piece Cable stripper KST 3 Article number 695020385
Instruction video	Instruction card	
www.hirschmann-multimedia.net/ montagefilm	www.hirschmann-multimedia.net/ installation/installatie-schema	
Productsheet MFC 1861	Article number 695020464	Version 07.2014-1.0 Page 1 / 2

WWW.HIRSCHMANN-MULTIMEDIA.NET

Maabaaiaal		VA (initial and in any set	
Mechanical	PRODUCTSHEET	Wiring diagram	
Specifications		CAI S.O.P.	
Dimensions hxwxd 135 x 61 x 40 mm	MFC 1861		
Weight	MULTITAP		
0.32 kg	6-WAY		
Color Metallic		20 dB amplifier with KOKA 9TS - 12.5dB - 13.5dB - 13.5dB - 14.5dB Max. 43m. Max. 102m. - Max. 96m. Max. 96m.	
Specifications		$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	
Mechanical specification Housing Material Finishing Connectors	Zinc die casting CuSn plated F-female	Max. 14m. Max. 72m. RFC 75	
Electrical specification Tap Loss			
in tap 1 in tap 2 in tap 3 in tap 4 in tap 5 in tap 6	12.5 dB 13.5 dB 14.5 dB 15.5 dB 16.5 dB 17.0 dB	▲ 12.5 ▲ 13.5 ▲ 15.5 ▲ 17.5 ▲ IN ▼ 14.5 ▼ 16.5 ▼ 6 OUT	
Loop through Insertion loss in-out	6 dB 5 - 40 MHz 5.3 dB 40 - 862 MHz 5.3 dB 862 - 1006 MHz 5.3 dB 1006 - 1200 MHz 5.3 dB	Related product - POFC 070 Article number 695002566	
Isolation Out - Tap	5 - 40 MHz > 30 dB 40 - 470 MHz > 30 dB 470 - 1006 MHz > 26 dB 1006 - 1200 MHz > 20 dB		
Тар - Тар	5 - 40 MHz > 40 dB 40 - 470 MHz > 40 dB 470 - 862 MHz > 36 dB 862 - 1200 MHz > 32 dB	Related product - KOKA 9 TS Article number 198799801	
Return Loss all ports	5 - 40 MHz > 18dB 40 - 1006 MHz > 20dB 1006 - 1200 MHz > 18 dB	Article number 198799801	
Screening (EN50083-2) Impedance	Class A 75 Ohm	Related product - EDC 1000 Article number 940442001	
Contact		Hirschmann Multimedia B.V.	
 Pampuslaan 170 1382 JS WEESP info@hirschmann. 		Hirschmann Multimedia B.V. is an international knowledge company and manufacturer, located in Weesp - The Netherlands. Hirschmann Multimedia focusses on leading the market by being innovative, flexible and renewing.	
f www.facebook.com		Hirschmann Multimedia Products (HMP): Serving the retail and installer market, Hirschmann Multimedia Products is expanding from The Netherlands and Belgium towards 16 other European countries as of 2014. Through a qualified and selected dealer and installer network, HMP provides in products for COAX, IP and satellite systems.	
Productsheet MFC 1861	Article number 695020464	Version 07.2014-1.0 Page 2 / 2	

© Copyright 2014 Hirschmann Multimedia B.V. All rights reserved. This document is for informational purposes only. Specifications and features can be subject to change without notice. Company name Hirschmann Multimedia B.V. and trade marks are registered in The Netherlands and Europe. For general terms and conditions of sale and delivery: www.hirschmann-multimedia.net.