HIRSCHMANN

MULTIMEDIA



Mechanical			Wiring diagram
Specifications			
Dimensions hxwxd 163x90x55mm	DFC 2104	shop	
	CATV 2-W	AY	
Weight 0.08 kg	SPLITTER		
			5 - 1250 MHz
Specifications			▼ 3.7 dB ▼ 3.7 dB
Mechanical specification Housing Material Zinc Die-casting Finishing CuSn plating			Values @ 862 MHz
	F female		
Insertion loss In-Out	Frequency range 5-860 MHz 860-1006 MHz 1006-1250 MHz	Specification < 4.0 dB < 4.3 dB < 5.0 dB	
Out-Out	5-15 MHz 15-40 MHZ 40-1250 MHz 5-40 MHz	> 20 dB > 26 dB > 26 dB* > 18 dB	Related product - KOKA 9 Eca/100 m white Article number 298799801 www.hirschmann-multimedia.com/CPR
	40-1218 MHz	> 18 dB*	Related product -
Screening (EN 50083-2) Impedance *- 1,5 dB/oct.		Class A+ 75 Ohm	QFC 5 shop Article number 695021145
			Related product - EDC 1000 shop Article number 695003008
Contact			Hirschmann Multimedia B.V.
 Pampuslaan 170 1382 JS WEESP info@hirschmann.nl NL 31 (0)294 46 25 55 BE 32 (0)2 46 13 095 www.linkedin.com/company/hirschmann-multimedia www.facebook.com/hirschmann.multimedia 			 Hirschmann Multimedia B.V. is an international knowledge company and manufacturer, located in Weesp - The Netherlands. Hirschmann Multimedia focusses on leading the market by being innovative, flexible and renewing. Hirschmann Multimedia Products (HMP): Serving the retail and installer market, Hirschmann Multimedia Products is expanding from The Netherlands and Belgium towards 16 other European countries as of 2014. Through a qualified and selected dealer and installer network,
Productsheet DFC 2104 sh	lirschmannMultimedia op Article num	HMP provides in products for COAX, IP and satellite systems. Version 07.2017-1.0 Page 2/2	

© Copyright 2014 Hirschmann Multimedia B.V. All rights reserved. This document is for informational purposes only. Specifications and features can be subject to change without notice. Company name Hirschmann Multimedia B.V. and trade marks are registered in The Netherlands and Europe. For general terms and conditions of sale and delivery: www.hirschmann-multimedia.net.